

Features

- Up to 14A Output Current
- +12V Input
- 93% Efficiency (PT6724)
- On/Off Standby Function
- Differential Remote Sense
- Adjustable Output Voltage
- Short Circuit Protection
- 17-pin Space-Saving Package
- Solderable Copper Case

Description

The PT6725 series of power modules are integrated switching regulators (ISRs), housed in a 17-pin space saving solderable copper package. These modules operate off a 12V input power bus to provide up to 14A of low-voltage power for the industry's latest high-speed, DSPs, μ Ps, and bus drivers. The series includes the standard output bus voltage options, ranging from 1.2V to 5.0V. The factory preset voltage can also be adjusted over a limited range with a single external resistor.

Features include a *Standby* function, output short circuit protection, and a differential *Remote Sense* to compensate for voltage drop between the ISR and load. The modules are available in both through-hole and surface mount configurations.

Ordering Information

PT6724□	= 5.0 Volts
PT6725□	= 3.3 Volts
PT6726□	= 2.5 Volts
PT6727□	= 1.8 Volts
PT6728□	= 1.5 Volts
PT6729□	= 1.2 Volts

PT Series Suffix (PT1234 x)

Case/Pin Configuration	Order Suffix	Package Code *
Vertical	N	(EMD)
Horizontal	A	(EMA)
SMD	C	(EMC)


* Previously known as package styles 1340/50.
(Reference the applicable package code drawing for the dimensions and PC board layout)

Pin-Out Information

Pin	Function
1	V_o Adjust
2	STBY*
3	Do Not Connect
4	V_{in}
5	V_{in}
6	V_{in}
7	Remote Sense Gnd
8	GND
9	GND
10	GND
11	GND
12	GND
13	V_{out}
14	V_{out}
15	V_{out}
16	V_{out}
17	Remote Sense V_{out}

* For further information, see application notes.

Standard Application



C_{in} = Required 1000 μ F electrolytic
 C_{out} = Required 330 μ F electrolytic
 L1 = Optional 1 μ H input choke

Specifications (Unless otherwise stated, $T_a = 25^\circ\text{C}$, $V_{in} = 12\text{V}$, $C_{in} = 1,000\mu\text{F}$, $C_{out} = 330\mu\text{F}$, and $I_o = I_{o,max}$)

Characteristic	Symbol	Conditions	PT6725 SERIES			Units	
			Min	Typ	Max		
Output Current	I_o	$T_a = +60^\circ\text{C}$, 200LFM $T_a = +25^\circ\text{C}$, natural convection	$V_o \leq 2.5\text{V}$ $V_o > 2.5\text{V}$	0.1 ⁽¹⁾ 0.1 ⁽¹⁾	— —	14 13	A
Input Voltage Range	V_{in}	Over I_o Range		10.8	—	13.2	VDC
Set Point Voltage Tolerance	$V_o \text{ tol}$			—	± 1	± 1.5 ⁽²⁾	% V_o
Temperature Variation	Reg_{temp}	$-40^\circ \leq T_a \leq +85^\circ\text{C}$, $I_o = I_{o,min}$		—	± 0.5	—	% V_o
Line Regulation	Reg_{line}	Over V_{in} range		—	± 5	± 10	mV
Load Regulation	Reg_{load}	Over I_o range		—	± 5	± 10	mV
Total Output Voltage Variation	$\Delta V_o \text{ tot}$	Includes set-point, line, load, $-40^\circ \leq T_a \leq +85^\circ\text{C}$		—	± 2	± 3	% V_o
Efficiency	η	$I_o = 9.0\text{A}$	$V_o = 5.0\text{V}$ $V_o = 3.3\text{V}$ $V_o = 2.5\text{V}$ $V_o = 1.8\text{V}$ $V_o = 1.5\text{V}$ $V_o = 1.2\text{V}$	— — — — — —	93 90 87 84 81 78	— — — — — —	%
V_o Ripple (pk-pk)	V_r	20MHz bandwidth		—	35	—	mV _{pp}
Transient Response	t_{tr}	5A/ μs load step, 50% to 100% $I_{o,max}$		—	70	—	μs
	ΔV_{tr}	V_o over/undershoot		—	± 100	—	mV
Short Circuit Threshold	I_{sc} threshold			—	20	32	A
Switching Frequency	f_s	Over V_{in} and I_o range		300	350	400	kHz
Remote On/Off (Pin 2)		Referenced to $-V_{in}$ (pin 8)		—	—	Open ⁽³⁾	V
Input High Voltage	V_{IH}			—	—	+0.4	
Input Low Voltage	V_{IL}			-0.1	—	—	
Input Low Current	I_{IL}			—	-0.5	—	mA
Standby Input Current	$I_{in, standby}$	pins 2 & 8 connected		—	0.5	1.0	mA
External Output Capacitance	C_{out}	See application schematic		330	—	15,000	μF
External Input Capacitance	C_{in}	See application schematic		1,000	—	—	μF
Operating Temperature Range	T_a	Over V_{in} range		-40 ⁽⁴⁾	—	+85 ⁽⁵⁾	$^\circ\text{C}$
Storage Temperature	T_s	—		-40	—	+125	$^\circ\text{C}$
Reliability	MTBF	Per Bellcore TR-332 50% stress, $T_a = 40^\circ\text{C}$, ground benign		7.8	—	—	10^6 Hrs
Mechanical Shock	—	Per Mil-Std-883D, method 2002.3, 1ms, half-sine, mounted to a fixture		—	500	—	G's
Mechanical Vibration	—	Mil-Std-883D, Method 2007.2, 20-2000Hz, soldered in PCB		—	15 ⁽⁶⁾	—	G's
Weight	—			—	23	—	grams
Flammability	—	Materials meet UL 94V-0		—	—	—	

Notes: (1) The ISR will operate at no load with reduced specifications.

(2) If the remote sense feature is not being used, connect the Remote Sense Gnd (pin 7) to GND (pin 8) for optimum output voltage accuracy.

(3) The STBY* control (pin 2) has an internal pull-up and if it is left open circuit the module will operate when input power is applied. The open-circuit voltage is typically the input voltage, V_{in} . Refer to the application notes for other interface considerations.

(4) For operation below 0°C , C_{in} and C_{out} must have stable characteristics. Use either low ESR tantalum or Oscon® capacitors. See application notes.




(5) See Safe Operating Area curves or contact the factory for the appropriate derating.

(6) The case pins on through-hole package types (suffixes N & A) must be soldered. For more information see the applicable package outline drawing.





Input/Output Capacitors: For proper operation in all applications, the PT6725 series requires a 1,000 μF input capacitor (C_{in}) with a minimum 1.6Arms ripple current rating. And a 330 μF output capacitor (C_{out}) with a maximum ESR of 50m Ω at 100kHz. For transient or dynamic load applications, additional output capacitance may be necessary. The maximum allowable output capacitance is 15,000 μF . For more information consult the related application note on capacitor recommendations.

Input Inductor: An input filter inductor is optional for most applications. The inductor must be sized to handle 6.5ADC with a typical value of 1 μH .

Characteristic Data; $V_{in} = 12V$ (See Note A)



Safe Operating Area; $V_{in} = 12V$ (See Note B)



Note A: Characteristic data has been developed from actual products tested at 25°C. This data is considered typical data for the Converter.

Note B: SOA curves represent the conditions at which internal components are at or below the manufacturer's maximum operating temperatures

Capacitor Recommendations for the 12V-Input PT6721/22 and PT6725 Series of ISRs

Input Capacitors

The recommended input capacitor(s) is determined by 1.6Arms minimum ripple current rating and 1,000 μ F minimum capacitance. Ripple current and Equivalent Series Resistance (ESR) values are the major considerations along with temperature when selecting the proper capacitor. The tantalum capacitors listed below cannot be used on the input bus since they are not rated for 12V operation.

Output Capacitors

The minimum required output capacitance is 330 μ F with a maximum ESR less than or equal to 50m Ω . Failure to observe this requirement may lead to regulator instability or oscillation. Electrolytic capacitors have poor ripple performance at frequencies greater than 400kHz, but excellent low frequency transient response. Above the ripple frequency ceramic decoupling capacitors are necessary to improve the transient response and reduce any microprocessor high frequency noise components apparent during higher current excursions. Preferred low ESR type capacitor part numbers are identified in the Table 1 below.

Tantalum Characteristics

Tantalum capacitors are recommended on the output bus but only AVX TPS Series, Sprague 593D/594/595 Series, or Kemet T495/T510 Series. These capacitors are recommended over other types due to their higher surge current, excellent power dissipation and ripple current ratings. As a caution, the TAJ Series by AVX is not recommended. This series exhibits considerably higher ESR, reduced power dissipation and lower ripple current capability. The TAJ Series is also less reliable compared to the TPS series when determining power dissipation capability.

Capacitor Table

Table 1 identifies the characteristics of capacitors from a number of vendors with acceptable ESR and ripple current (rms) ratings. The suggested minimum quantities per regulator for both the input and output buses are identified.

This is not an extensive capacitor list. Capacitors from other vendors are available with comparable specifications. Those listed are for guidance. The RMS ripple current rating and ESR (Equivalent Series Resistance at 100kHz) are the critical parameters are necessary to insure both optimum regulator performance and long capacitor life.

Table 1 Capacitors Characteristic Data

Capacitor Vendor/ Series	Capacitor Characteristics					Quantity		Vendor Part Number
	Working Voltage	Value(μ F)	(ESR) Equivalent Series Resistance	105°C Maximum Ripple Current(Irms)	Physical Size(mm)	Input Bus	Output Bus	
Panasonic FC (Radial) FC/FK (Surface Mount)	35V	680	0.043 Ω	1655mA	12.5x20	2	1	EEUFC1V681
	25V	1000	0.038 Ω	1655mA	12.5x20	1	2	EEUFC1E102
	25V	1000	0.038 Ω	1690mA	16x15	1	1	EEUFC1E102S
	50V	1000	0.073 Ω	1610mA	16x16.5	1	1	EEVFK1H102M
	25V	1000	0.038 Ω	2000mA	18x16.5	1	1	EEVFC1E102N
	35V	470	0.043 Ω	1690mA	16x16.5	2	1	EEVFC1V471N
United Chemi-con LXV Series	35V	680	0.034 Ω	1690mA	12.5x25	2	1	LXV35VB680M12X25LL
	35V	1000	0.038 Ω	1630mA	16x20	1	1	LXV35VB102M16X20LL
	16V	470	0.084 Ω +2 =0.042 Ω	825mA (x2)	10x16	2	1	LXV16VB471M10X16LL
Nichicon PL Series PM Series	35V	680	0.036 Ω	1660mA	12.5x25	2	1	UPL1V681MHH
	25V	1200	0.039 Ω	1600mA	18x15	1	1	UPL1E122MHH6
	35V	1000	0.034 Ω	1770mA	16x20	1	1	UPM1V102MHH6
Os-con: SS SV (surface Mount)	10V	330	0.025 Ω	3500mA	10x10.5	N/R(1)	1	10SS330M (V _o <5V)
	10V	330	0.020 Ω	3800mA	10.3x10.3	N/R(1)	1	10SV330 (V _o <5V)
AVX Tantalum TPS (Surface Mount)	10V	330	0.1 Ω +2 =0.05 Ω	>2500mA	7.3L	N/R(1)	2	TPSE337M010R0100
	10V	330	0.06 Ω +2 =0.03 Ω	>3000mA	\times 5.7W \times 4.1H	N/R(1)	2	TPSV337M010R0060
Kemet Tantalum T510/T495 Series (Surface Mount)	10V	330	0.033 Ω	1400mA	4.3W	N/R(1)	1	510X337M010AS
	10V	220	0.07 Ω +2 =0.035 Ω	>2000mA	\times 7.3L \times 4.0H	N/R(1)	2	T495X227M0100AS
Sprague Tantalum 594D Series (Surface Mount)	10V	330	0.045 Ω	2360mA	7.2L \times 6W \times 4.1H	N/R(1)	1	594D337X0010R2T

Note: (N/R -Not recommended) The 10V-rated tantalum capacitors cannot be used on the input bus.

Using the Standby Function of the PT6725 Series of Integrated Switching Regulators

The PT6725 series of power modules are high efficiency regulators that operate off a +12V input bus voltage. These regulators incorporate an on/off 'Standby' function, which may be used to disable the regulator output.

The standby function is provided by the *STBY** control, pin 2. If pin 2 is left open-circuit the regulator operates normally, and provides a regulated output when a valid supply voltage is applied to V_{in} (pins 4–6) with respect to GND (pins 8–12). If a low voltage³ is then applied to pin 2 the regulator output will be disabled and the input current drawn by the ISR will be reduced to 0.5mA¹. The standby control may also be used to hold-off the regulator output during the period that input power is applied.

Pin 2 is ideally controlled with an open-collector (or open-drain) discrete transistor (See Figure 1). The open-circuit voltage is typically the input voltage V_{in} . Table 1 gives the circuit parameters for this control input.


Table 1 Standby Control Requirements ^(2, 3)

Parameter	Min	Typ	Max
Input Low (V_{IL})	-0.1V		+0.4V
I_{stby} (pin 2 =ground)	—	-0.5mA	—
V_{stby} (open circuit)	—	V_{in}	—

Notes:


1. When the regulator output is disabled the current drawn from the + V_{in} input source is typically reduced to 0.5mA.
2. The standby control input requires no external pull-up resistor. The open-circuit voltage of the *STBY** pin is approximately the input voltage V_{in} (+12V).
3. The standby control input is Not compatible with TTL devices that incorporate a totem-pole output drive. Use only a true open-collector device, preferably a discrete bipolar transistor (or MOSFET). To ensure the regulator output is disabled, the control pin must be pulled to less than 0.4Vdc with a low-level 0.5mA sink to ground.
4. After Q_1 in Figure 1 is turned off and before the output begins to rise, the regulator output will assert a low impedance to ground. If an external voltage is applied to the output it will sink current and possibly over-stress the part.

Figure 1



Turn-On Time: In the circuit of Figure 1, turning Q_1 on applies a low voltage to the *STBY* control (pin 2) and disables the regulator output. Correspondingly, turning Q_1 off removes the low-voltage signal and enables the output. Once enabled, the output will typically experience a 10–15ms delay followed by a predictable ramp-up of voltage. The regulator should provide a fully regulated output voltage within 30ms. Figure 2 shows the output voltage response, V_o , of a PT6726 (2.5V) following the turn-off of Q_1 . The turn-off of Q_1 corresponds to the rise in V_{stby} . The waveform was measured with a 12Vdc input voltage, and 9.3ADC resistive load.

Figure 2



Adjusting the Output Voltage of the PT6725 Series of Integrated Switching Regulators

The PT6725 series of ISRs are non-programmable versions of the PT6721/2 Excalibur™ regulators. The regulators have a fixed output voltage, which may be adjusted higher or lower than the factory pre-set voltage using a single external resistor. Table 1 gives the adjustment range for each model in the series as V_a (min) and V_a (max).

Adjust Up: An increase in the output voltage is obtained by adding a resistor R_2 , between pin 1 (V_o Adjust) and pin 7 (Remote Sense GND).

Adjust Down: Add a resistor (R_1), between pin 1 (V_o Adjust) and pin 17 (Remote Sense V_{out}).

Refer to Figure 1 and Table 2 for both the placement and value of the required resistor, either (R_1) or R_2 as appropriate.


The values of (R_1) [adjust down], and R_2 [adjust up], can also be calculated using the following formulas.

$$(R_1) = \frac{R_o (V_a - V_r)}{V_o - V_a} - R_s \quad \text{k}\Omega$$

$$R_2 = \frac{R_o \cdot V_r}{V_a - V_o} - R_s \quad \text{k}\Omega$$

Where: V_o = Original output voltage
 V_a = Adjusted output voltage
 V_r = The reference voltage (Table 1)
 R_o = The multiplier resistance (Table 1)
 R_s = The internal series resistance (Table 1)

Figure 1



Notes:

1. Use only a single 1% resistor in either the (R_1) or R_2 location. Place the resistor as close to the regulator as possible.
2. Never connect capacitors from V_o Adjust to either GND, V_{out} , or the Remote Sense pins. Adding capacitance to the V_o Adjust pin will affect the stability of the ISR.
3. If the Remote Sense feature is not being used, pin 7 must be connected to pin 8 for optimum output voltage accuracy. The resistors (R_1) and R_2 may then be connected from ' V_o Adjust' to either V_{out} or GND respectively.

PT6705/PT6715 Series

Table 1

ADJUSTMENT AND FORMULA PARAMETERS

Series Pt #	PT6729	PT6728	PT6727	PT6726	PT6725	PT6724
V_o (nom)	1.2	1.5	1.8	2.5	3.3	5.0
V_a (min)	1.09	1.47	1.75	2.25	2.75	4.01
V_a (max)	1.52	1.73	2.0	2.85	3.75	5.47
V_r (V)	0.8	1.27	1.27	1.27	1.27	1.27
R_o (kΩ)	10.0	10.2	10.0	10.0	10.0	9.09
R_s (kΩ)	24.9	49.9	49.9	33.2	24.9	24.9

Table 2

ADJUSTMENT RESISTOR VALUES

Series Pt #	PT6729	PT6728	PT6727	PT6726	Series Pt #	PT6725	PT6724
V_o (nom)	1.2V	1.5V	1.8V	2.5V	V_o (nom)	3.3V	5.0
V_a (req'd)					V_a (req'd)		
1.1	(5.1)kΩ				2.75	(2.0)kΩ	
1.15	(45.1)kΩ				2.8	(5.7)kΩ	
1.2					2.85	(10.2)kΩ	
1.25	135.0kΩ				2.9	(15.9)kΩ	
1.3	55.1kΩ				2.95	(23.1)kΩ	
1.35	28.4kΩ				3.0	(32.8)kΩ	
1.4	15.1kΩ				3.05	(46.3)kΩ	
1.45	7.1kΩ				3.1	(66.6)kΩ	
1.47	4.7kΩ	(18.1)kΩ			3.15	(100.0)kΩ	
1.5	1.8kΩ				3.2	(168.0)kΩ	
1.55		209.0kΩ			3.25	(371.0)kΩ	
1.6		79.6kΩ			3.3		
1.65		36.5kΩ			3.35	229.0kΩ	
1.7		14.9kΩ			3.4	102.0kΩ	
1.75			(46.1)kΩ		3.45	59.8kΩ	
1.8					3.5	38.6kΩ	
1.85			204.0kΩ		3.55	25.9kΩ	
1.9			77.1kΩ		3.6	17.4kΩ	
1.95			34.8kΩ		3.65	11.4kΩ	
2.0			13.6kΩ		3.7	6.9kΩ	
2.05					3.75	3.3kΩ	
2.1					.		
2.15					4.1		(3.7)kΩ
2.2					4.2		(8.4)kΩ
2.25				(6.0)kΩ	4.3		(14.4)kΩ
2.3				(18.3)kΩ	4.4		(22.5)kΩ
2.35				(38.8)kΩ	4.5		(33.8)kΩ
2.4				(79.8)kΩ	4.6		(50.8)kΩ
2.45				(203.0)kΩ	4.7		(79.0)kΩ
2.5					4.8		(136.0)kΩ
2.55				221.0kΩ	4.9		(305.0)kΩ
2.6				93.8kΩ	5.0		
2.65				51.5kΩ	5.1		90.5kΩ
2.7				30.3kΩ	5.2		32.8kΩ
2.75				17.6kΩ	5.3		13.6kΩ
2.8				9.1kΩ	5.4		4.0kΩ
2.85				3.1k			

R1 = (Blue) R2 = Black

PACKAGING INFORMATION

Orderable Device	Status (1)	Package Type	Package Drawing	Pins	Package Qty	Eco Plan (2)	Lead/Ball Finish	MSL Peak Temp (3)	Samples (Requires Login)
PT6724N	LIFEBUY	SIP MODULE	EMD	17	10	Pb-Free (RoHS)	Call TI	N / A for Pkg Type	
PT6725C	LIFEBUY	SIP MODULE	EMC	17	10	Pb-Free (RoHS)	Call TI	Level-3-215C-168HRS	

(1) The marketing status values are defined as follows:

ACTIVE: Product device recommended for new designs.

LIFEBUY: TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.

NRND: Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.

PREVIEW: Device has been announced but is not in production. Samples may or may not be available.

OBSELETE: TI has discontinued the production of the device.

(2) Eco Plan - The planned eco-friendly classification: Pb-Free (RoHS), Pb-Free (RoHS Exempt), or Green (RoHS & no Sb/Br) - please check <http://www.ti.com/productcontent> for the latest availability information and additional product content details.

TBD: The Pb-Free/Green conversion plan has not been defined.

Pb-Free (RoHS): TI's terms "Lead-Free" or "Pb-Free" mean semiconductor products that are compatible with the current RoHS requirements for all 6 substances, including the requirement that lead not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, TI Pb-Free products are suitable for use in specified lead-free processes.

Pb-Free (RoHS Exempt): This component has a RoHS exemption for either 1) lead-based flip-chip solder bumps used between the die and package, or 2) lead-based die adhesive used between the die and leadframe. The component is otherwise considered Pb-Free (RoHS compatible) as defined above.

Green (RoHS & no Sb/Br): TI defines "Green" to mean Pb-Free (RoHS compatible), and free of Bromine (Br) and Antimony (Sb) based flame retardants (Br or Sb do not exceed 0.1% by weight in homogeneous material)

(3) MSL, Peak Temp. -- The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services per JESD46, latest issue, and to discontinue any product or service per JESD48, latest issue. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All semiconductor products (also referred to herein as "components") are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its components to the specifications applicable at the time of sale, in accordance with the warranty in TI's terms and conditions of sale of semiconductor products. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by applicable law, testing of all parameters of each component is not necessarily performed.

TI assumes no liability for applications assistance or the design of Buyers' products. Buyers are responsible for their products and applications using TI components. To minimize the risks associated with Buyers' products and applications, Buyers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI components or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of significant portions of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI components or services with statements different from or beyond the parameters stated by TI for that component or service voids all express and any implied warranties for the associated TI component or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Buyer acknowledges and agrees that it is solely responsible for compliance with all legal, regulatory and safety-related requirements concerning its products, and any use of TI components in its applications, notwithstanding any applications-related information or support that may be provided by TI. Buyer represents and agrees that it has all the necessary expertise to create and implement safeguards which anticipate dangerous consequences of failures, monitor failures and their consequences, lessen the likelihood of failures that might cause harm and take appropriate remedial actions. Buyer will fully indemnify TI and its representatives against any damages arising out of the use of any TI components in safety-critical applications.

In some cases, TI components may be promoted specifically to facilitate safety-related applications. With such components, TI's goal is to help enable customers to design and create their own end-product solutions that meet applicable functional safety standards and requirements. Nonetheless, such components are subject to these terms.

No TI components are authorized for use in FDA Class III (or similar life-critical medical equipment) unless authorized officers of the parties have executed a special agreement specifically governing such use.

Only those TI components which TI has specifically designated as military grade or "enhanced plastic" are designed and intended for use in military/aerospace applications or environments. Buyer acknowledges and agrees that any military or aerospace use of TI components which have **not** been so designated is solely at the Buyer's risk, and that Buyer is solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI has specifically designated certain components as meeting ISO/TS16949 requirements, mainly for automotive use. In any case of use of non-designated products, TI will not be responsible for any failure to meet ISO/TS16949.

Products

Audio	www.ti.com/audio
Amplifiers	amplifier.ti.com
Data Converters	dataconverter.ti.com
DLP® Products	www.dlp.com
DSP	dsp.ti.com
Clocks and Timers	www.ti.com/clocks
Interface	interface.ti.com
Logic	logic.ti.com
Power Mgmt	power.ti.com
Microcontrollers	microcontroller.ti.com
RFID	www.ti-rfid.com
OMAP Applications Processors	www.ti.com/omap
Wireless Connectivity	www.ti.com/wirelessconnectivity

Applications

Automotive and Transportation	www.ti.com/automotive
Communications and Telecom	www.ti.com/communications
Computers and Peripherals	www.ti.com/computers
Consumer Electronics	www.ti.com/consumer-apps
Energy and Lighting	www.ti.com/energy
Industrial	www.ti.com/industrial
Medical	www.ti.com/medical
Security	www.ti.com/security
Space, Avionics and Defense	www.ti.com/space-avionics-defense
Video and Imaging	www.ti.com/video

TI E2E Community

e2e.ti.com