


Heptoda

1LA6


Mieszacz i oscylator

Loktal



$$U_z = 14V$$

$$I_z = 0,05A$$



Wartości robocze

| | | |
|------------|---------------|------------|
| U_b | 90 | V |
| U_a | 90 | V |
| U_{s2} | 90 | V |
| $U_{s3,5}$ | 45 | V |
| U_{s1} | 0... -3 | V |
| I_a | 0,55 | mA |
| I_{s2} | 1,2 | mA |
| $I_{s3,5}$ | 0,6 | mA |
| S_p | 0,25 ... 0,01 | mA/V |
| ρ_a | 750 | k Ω |
| R_{s1} | 200 | k Ω |
| $R_{s3,5}$ | 70 | k Ω |

Wartości maksymalne

| | | |
|----------------|-----|----|
| $U_{a,max}$ | 110 | V |
| $U_{s2,max}$ | 90 | V |
| $U_{s3,5,max}$ | 60 | V |
| $I_{k,max}$ | 4 | mA |

TYPY PODOBNE

1 A 7-GT, 1 LA 6 E