


Pentoda

6BH6


Wzmacniacz w.cz. kl. A

Miniaturowy



$$U_z = 6,3V$$

$$I_z = 0,15A$$



Wartości robocze

U_a	100	250	V
U_{s3}	0	0	V
U_{s2}	100	150	V
U_{s1}	-1	-1	V
$U_{s1}^{1)}$	-5	-7,7	V
I_a	3,6	7,4	mA
I_{s2}	1,4	2,9	mA
S_a	3,4	4,6	mA/V
ρ_a	0,7	1,4	M Ω

¹⁾ Przy $I_a = 10 \mu A$.

Wartości maksymalne

U_{amax}	300	V
U_{s2bmax}	300	V
U_{s1min}	-50	V
U_{s1max}	0	V
P_{amax}	3	W
U_{wlkmax}	90	V

Pojemności

	Z ekranem zewnątrzn.	Bez ekranu zewnątrzn.	
C_{wej}	5,4	5,4	pF
C_{wyj}	4,4	4,4	pF
$C_{s1/a}$	0,0035	0,0035	pF

TYPY PODOBNE

6661, 6AG5, E90F

