


Pentoda regulacyjna

6BJ6


Wzmacniacz w.c.z. kl. A

Miniaturowy



$$U_z = 6,3 V$$

$$I_z = 0,15 A$$



Wartości robocze

U_a	100	250	V
U_{s3}	0	0	V
U_{s2}	100	100	V
U_{s1}	-1...-20	-1...-20	V
I_a	9 —	9,2 —	mA
I_{s2}	3,5 —	3,3 —	mA
S_a	3,65...0,01	3,6... 0,01	mA/V
ρ_a	0,25 —	1,3 —	M Ω

Wartości maksymalne

U_{amax}	300	V
U_{s2bmax}	300	V
U_{s2max}	125	V
U_{s1min}	-50	V
U_{s1max}	0	V
P_{amax}	3	W
U_{wkmax}	90	V

Pojemności

C_{wej}	4,5	pF
C_{wyj}	5,5	pF
$C_{s1/a}$	0,0035	pF

TYPY PODOBNE

6662, E 99 F, EF 93

