


Trioda

L77

Marconi


Wzmacniacz mocy, oscylator

Miniaturowy



$$\frac{U_{\dot{z}}}{I_{\dot{z}}} = 6,3V$$

$$I_{\dot{z}} = 150mA$$



Wartości robocze

kl. A

kl. C

| | | | | |
|-----------|------|------|------|------------|
| U_a | 100 | 250 | 300 | V |
| U_s | 0 | -8,5 | -27 | V |
| I_a | 12 | 10,5 | 25 | mA |
| I_s | — | — | 7 | mA |
| S_a | 3,1 | 2,2 | — | mA/V |
| K_a | 19,5 | 17 | — | V/V |
| Q_a | 6,25 | 7,7 | — | k Ω |
| P_{wyj} | — | — | 5,5 | W |
| P_{wej} | — | — | 0,35 | W |

Wartości graniczne

| | | |
|---------------|-----|------------|
| $U_{a\max}$ | 300 | V |
| $P_{a\max}$ | 3,5 | V |
| $U_{w/k\max}$ | 150 | V |
| $R_{s1\max}$ | 1 | M Ω |

Pojemności

| | | |
|------------|-----|----|
| C_{wej} | 1,7 | pF |
| C_{wyj} | 2,6 | pF |
| $C_{s1/a}$ | 2,0 | pF |

TYPY PODOBNE

EC 90