



T.			U_f	I_f	U_a	U_{g2}	U_{g1}	I_a	I_{g2}	S	R_i	R_k	P_a	P_{g2}^-
			V	A	V	V	V	mA	mA	mA/V	M Ω	Ω	W	W
EF 731 5900¹⁾	eur amer	1 2	6,3 6,3	0,15 0,15	$\left\{ \begin{array}{l} 100 \\ 165 \end{array} \right.$	100 155	$-1,2 \div -14$ maximum	7,2 $(I_k = 16,5 \text{ mA})$	2,2	$4,5 \div 0,025$	0,26	120	1,1	0,55

T.	$C_{g1/k}$	$C_{a/k}$	$C_{g1/a}$	vide
	pF	pF	pF	
EF 731	4 4,3	1,9 3,4	0,03 0,015	*5 *6

Equivalents EF 731

EF 71 EF 761³⁾	eur RFT	5899²⁾	int
--	------------	--------------------------	-----

¹⁾ vide *4, a, b, c ($U_f = 6,3 \text{ V} \pm 10\%$)

²⁾ vide *4, a, b, c, d, e, f, g ($U_f = 6,3 \text{ V} \pm 5\%$)

³⁾ vide *4

