



T.			U_f	I_f	U_a	U_g	I_a	S	μ	R_i
			V	A	V	V	mA	mA/V	V/V	k Ω
BO	Sim	1	1,7	0,07	135	- 2	1	0,6	25	40
F 109	Phl	1	1,5	1,05	90	-10	5,5	1,1	8,3	7,6
26	amer	2	1,5	1,05	180	-14,5	6,2	1,15	8,3	7,3
264 C ¹⁾	WE	2	1,5	0,3	100	- 8	2,1	0,58	7,2	12,4

¹⁾ vide *4

Equivalentents

DY 1210	Mul = BO	R 88	Dar = BO	264 E	WE = 264C
F 109 A	Phl = 26	RV 222	Tlf = BO	326	amer = 26
FP 58	amer = 26	T 26	amer = 26	426	amer = 26
G 26	amer = 26	126	amer = 26	2260	amer = 26
KL 70401	Kgf = BO	226	amer = 26	4264 A	STCE = 264C
LX 2260	Tu = 26	264 A	WE = 264 C	70401	Kgf = BO
M 26	amer = 26	264 B	WE = 264 C	38026	amer = 26

