



T.			U_f	I_f	U_a	U_{g2}	U_{g3+5}	U_{g4}	I_a	I_{g2}	I_{g3+5}	I_{g1}	S_c	R_i	R_{g1}	U_{osc}
			V	A												
AK 1	eur	1	4	0,65	250	90	70	-1,5 ÷ -25	1,6	2	3,8	0,19	600 ÷ 2	1,6	50	8,5
AK 2	eur	2	4	0,65												
FC 4	Mul	3	4	0,65												
MO 465	Tu	4	4	0,65												

maximum ($I_k = 10 \text{ mA}$; $P_a = P_{g3+5} = 0,5 \text{ W}$; $P_{g2} = 0,3 \text{ W}$; $U_{f/k} = 50 \text{ V}$)

Equivalents

A 4-GDR	Cas = AK 2	OV 4110	Vat = AK 2	TK 24	Imp = AK 2
A 80 A	ER = FC 4	SO 4100	Vat \approx AK 2	VO 4	Tu = FC 4
D 407	Tu = MO 465	T 4000 N	Fot \approx AK 2	VO 4 S	Tu = AK 2
NMO 46	Sat = AK 1	TAK 1	Tu = AK 1	3 M 1	Low = AK 2
NMO 51	Sat = AK 2	TAK 2	Tu = AK 2	4 A 12	Ult \approx AK 2
O 406	Tri \approx AK 2	TE 504	Dar \approx FC 4	4 A 16	Ult = AK 2
O 407	Tri = AK 2	TK 1	Dar = AK 1	4 M 1	Low = AK 2
OV 4100	Vat = AK 2	TK 2	Dar = AK 2	41 PGDD	Cos = FC 4

