

Pentoda


1LC5

Wzmacniacz kl. A

Loktal

1LC5

$$U_z = 1,4 \text{ V}$$
$$I_z = 0,05 \text{ A}$$



Wartości robocze

Wartości maksymalne

$U_a$	45	90	V
$U_{s2}$	45	45	V
$U_{s1}$	0	0	V
$I_a$	1,1	1,15	mA
$I_{s2}$	0,35	0,30	mA
$S_a$	0,750	0,775	mA/V
$\rho_a$	0,7	1,5	M $\Omega$
$R_{s1}$	1	1	M $\Omega$

$U_{amax}$	110	V
$U_{s2max}$	45	V

Pojemności

$C_{wej}$	3,2	pF
$C_{uyj}$	7,0	pF
$C_{s1/a}$	0,007	pF

TYPY PODOBNE