


# Pentoda mocy


**1 П 3 Б**  
**(1 P 3 B)**

Wzmacniacz mocy m.cz.

Bez cokołu



$U_z = 1,25V$   
 $I_z = 27mA$



## Wartości charakterystyczne i robocze

|           |                     |           |
|-----------|---------------------|-----------|
| $U_a$     | 45                  | V         |
| $U_{s2}$  | 45                  | V         |
| $U_{s1}$  | -2                  | V         |
| $I_a$     | 750<br>+300<br>-350 | $\mu A$   |
| $I_{s2}$  | $\leq 450$          | $\mu A$   |
| $S_a$     | $425 \pm 125$       | $\mu A/V$ |
| $P_{wyj}$ | $\geq 4,5$          | $\mu W$   |
| $h$       | $< 12$              | %         |

## Wartości graniczne

|            |      |   |
|------------|------|---|
| $P_{umax}$ | 0,05 | W |
|------------|------|---|

TYPY PODOBNE

**1 П 2 Б**

