

Pentoda

EF 21


TELAM

Wzmacniacz w. cz.

Loktal

EF21

$$\frac{U_{\dot{z}}}{I_{\dot{z}}} = 6,3V$$
$$I_{\dot{z}} = 200mA$$



Wartości charakterystyczne i robocze

U_a	250	V
I_a	6	mA
U_{s1}	-2,5	V
U_{s2}	100	V
I_{s2}	1,7	mA
S_a	2,2	mA/V
ρ_a	1,25	M Ω
R_k	325	Ω

TYPY PODOBNE

