

Pentoda

EL 172


RFT

Wzmacniacz mocy m. cz.

Gnom

EL172

$$\frac{U_{\dot{z}} = 6,3V}{I_{\dot{z}} = 1,2A}$$



Wartości robocze

U_a	250	V
I_a	72	mA
U_{s1}	—7	V
U_{s2}	250	V
U_{s3}	0	V
I_{s2}	8	mA
S_a	15	mA/V
ρ_a	30	k Ω
R_a	3	k Ω
R_k	90	Ω
P_a	18	W
P_{wyj}	8	W
U_{wej}	4,5	V _{sk}

TYPY PODOBNE

EL 12